

# LogiLink®

## 3V-12V Universal Power Adapter

7 Changeable Tips Included

Art. No.: PA0161




Ideal as a replacement or secondary power adapter for electronics and small home appliance.

### Features:

- » Provide different charger adapters for easily charging most of the digital devices
- » Reliable replacement or secondary power adapter in home or office
- » Built-in protection against over current, over voltage, over temperature and short-circuit protection



Home/Office



For digital camera, battery chargers, mobile phone, router, games console and many others

### Specification:

Input Voltage	AC 100-240V 50/60Hz 1A max
Output Power	DC 3V/4.5V/5V/6V/7.5V/9V/12V 2A (24W max)
Efficiency	83% max
Standby Power Loss	≤0.3W
Operating Temperature	0°C ~ 45°C
Operating Humidity	10% ~ 80%
Storage Temperature	-20°C ~ 85°C
Storage Humidity	10% ~ 93%
Dimension	92 x 46 x 36mm (not including cable)
Weight	0.127kg
Cable Length	1.5m



C	5.5 x 2.5mm
H	3.5 x 1.35mm
T	3.5mm Jack
G	4.0 x 1.7mm
L	3.0 x 1.1mm
I	2.5 x 0.7mm
S	Micro USB



PA0161



4 052792 047097

Made in China



RoHS compliant





\* The specifications and pictures are subject to change without notice.  
\*All trade names referenced are the registered namework of their respective owners.

# LogiLink®

## 3V-12V Universal Power Adapter

7 Changeable Tips Included

Art. No.: PA0161



### Package Contents:

- » 1 x Universal Power Adapter
- » 7 x Changeable Tips
- » 1 x Key
- » 1 x User Manual

### Package Informations:

- » Packing Dimension: 176 x 127.5 x 48.5mm
- » Packing Weight: 0.22kg
- » Carton Dimension: 440 x 370 x 390mm
- » Carton Q'ty: 60pcs
- » Carton Weight: 13.1kg

### Warning

- \*For use with Information Technology Equipment.
- \*Compare the specifications of your device with the specifications of the adapter. The power current (A) of your device should be equal to or lower than the power current of the power supply.
- \*Only to be used indoor.
- \*Only to be used after powering on.
- \*Only to be used within max load.
- \*Remove the power adapter from its power source after use.



Best Connectivity



RoHS  
compliant



\* The specifications and pictures are subject to change without notice.  
\*All trade names referenced are the registered namework of their respective owners.



PA0161



Made in China